

TA3660-T100

(1mmq)	MAINS/50Hz			ANODIC	(0,50mmq)
Brown	O	Common	330V	O	Red
Blue	O	230V	300mA	O	Gray
White	O	240V		ANODIC	(0,50mmq)
(0,50mmq)	BIAS		330V	O	Purple
Pink	O	55V	300mA	O	Black
Pink	O	500mA		HEATERS	(1,50mmq)
(1mmq)	HEATHER		3,20V	O	Green
Orange	O	5V	8A CT	O	Black
Orange	O	3A	3,20V	O	Green

Different versions of TWIN:

- TWIN 5F8A, with GZ34 tube rectifier. it is therefore necessary a secondary 5V @ 3A for heater, and secondary HT circuit for half-wave.
- TWIN REVERB AB 763, with secondary HT circuit for half-wave.
- TWIN REVERB Reissue, with secondary HT for the diode bridge (Graetz).

HT circuit for half-wave: Connect GRAY and PURPLE.

(RED) **330V**- (GRY / PPL) **0**- (BLK) **330V** @ 600mA

HT for circuit diode bridge: connect RED and PURPLE, GRAY and BLACK.

(RED / PPL) **330V**- (GRY / BLK) **0** @ 600mA