

http://www.tubeampdoctor.com/product_info.php?category_id=170&products_id=3047&mySID=tQZzGTFpLqPtzwGvAEjP80

Mains transf. for Mesa Boogie Transatlantic TA15

power transformer for Mesa Boogie Transatlantic TA15, MINI RECTIFIER® TWENTY-FIVE and MARK 5 TWENTY-FIVE

230/240V, #561841, comes without multi-pin connector and shrouds

Exportversion, replaces the 120V domestic version (561840)

Additional parts needed for conversion:

2x V-X-2

1x V-X-47

1x Z-VDR275

1x PC265

1x Z-USSI-T0.63A

Mounting on: 52mm x 56mm

Overall Dimensions W x H x D: 76mm x 68mm x 74mm

Primary:

240V White	24.19 Ohm
230V Grey	22.97
0V Brown	0

Secondary:

325V 70mA Red	193.2	
72V Blue	46.6	
0V Green/Yellow	0	(Red/Yellow color for original Mesa)
325V Red	223.53	
14V 0,5A Brown	0.98	
0V Brown	0	
3,15V 2,8A Green	0.09	
0V Green/Yellow	0	
3,15V Green	0.09	